

ADP-DAI-2X0 - Dante Adaptor



Dante(r) AVIO analogue input adapter (2-channel)

- For connecting analogue audio line level devices (e.g. mixer) to a Dante(r) audio network
- Adjustable signal level: +24/+4/0 dBu, 0/-10 dBV (via Dante(r) controller)
- Frequency range: 20-20,000 Hz
- Impedance: 20 kOhm (bal.), 10 kOhm (unbal.)
- Dynamic range: > 100 dB
- S/N ratio: > 100 dB
- THD: < 0.01%
- Sampling rates: 44.1/48/96 kHz, 24 bits
- Connections: 1 x RJ45, 2 x XLR inline jack

The brand Dante(r) as well as the Dante(r) software which may have been integrated into these products are licenced by Audinate Pty Ltd.

Tekniske data

| | |
|-----------------------|--|
| Description | : Dante ⁽ⁿ⁾ AVIO analogue input adapter |
| Nominal value | : - |
| Type | : 2-channel |
| Colour | : black |
| Material | : - |
| Suitable for | : - |
| Power supply | : PoE |
| Admiss. ambient temp. | : - |
| Dimensions | : - |
| Length | : - |
| Mounting dimensions | : - |
| Weight | : 165 g |
| Connections | : 1 x RJ45, 2 x 3-pole XLR inline jack |
| Other features | : - |
| Packing unit | : 1 |