

MMX-8 - Microphone Mixer



Miniature universal audio mixer

- 8 mono channels, switchable mic/line
- Selection of 4 stereo channels
- 2 output level controls, 2 peak LEDs
- Supplied w/o battery

Tekniske data

No. of channels	: -
No. of inputs	: -
Mic input	: 5Â mV, 8 x 6.3 mm jack
Line input	: 50Â mV, 8 x 6.3 mm jack
CD input	: -
Phono input	: -
Tape (play)	: -
Aux input	: -
Insert input	: -
Effect return	: -
Master output	: 100Â mV, 2 x 6.3 mm jack
Record output	: -
Monitor output	: -
Booth output	: -
Aux output	: -
Insert output	: -
Effect send	: -
Control room	: -
Tape (rec)	: -
Headphones	: -
Gooseneck lamp	: -
WiFi	: -
USB	: -
Bluetooth	: -
Frequency range	: 20-20,000Â Hz
THD	: < 0.4%
S/N ratio	: 55 dB
Crosstalk	: -
Equalizer bass	: -
Equalizer midrange	: -
Equalizer treble	: -
equalizer	: -
Talkover	: -
Phantom power	: -
Crossfader	: -

Media player	: -
Amplifier	: -
Power supply	: 9Â V battery or via optional power supply PSS-600E
Mains voltage	: -
Mains frequency	: -
Power consumption, operation	: -
Operating voltage (possible alternative)	: -
Power supply (possible alternative)	: -
Admiss. ambient temp.	: 0-40 °C
Width	: 150 mm
Height	: 68 mm
Depth	: 115 mm
Rack spaces, RS	: -
Weight	: 550 g